

XS LED RGB 3 Ch A Mode

DMX Channel	Function	Description	Value
1	Dimmer	Red intensity	0-255
2	Dimmer	Green intensity	0-255
3	Dimmer	Blue intensity	0-255

XS LED RGB 7 Ch B Mode

DMX Channel	Function	Description	Value
1	Dimmer	Master Dimmer	0-255
2	Intensity	Red intensity	0-255
3	Intensity	Green intensity	0-255
4	Intensity	Blue intensity	0-255
5	Duration	Flash Duration	0-255
6	Strobe	No Function	0-5
		Strobe Rate	6-255
7	Macro	No Function	0-5
		Ramp Up Effect (slow to fast)	6-42
		Ramp Down Effect (slow to fast)	43-85
		Ramp Up-Down Effect (slow to fast)	86-128
		Random Effect (slow to fast)	129-171
		Lightning Effect (slow to fast)	172-214
		Spike Effect	215-255

XS LED RGB 8 Ch C Mode

DMX Channel	Function	Discription	Value
1	Dimmer	No Function	0-255
2	Intensity	Red intensity	0-255
3	Intensity	Green intensity	0-255
4	Intensity	Blue intensity	0-255
5	Duration	Flash Duration	0-255
6	Strobe	No Function	0-5
		Strobe Rate	6-255
7	Macro	No Function	0-5
		Ramp Up Effect (slow to fast)	6-42
		Ramp Down Effect (slow to fast)	43-85
		Ramp Up-Down Effect (slow to fast)	86-128
		Random Effect (slow to fast)	129-171
		Lightning Effect (slow to fast)	172-214
		Spike Effect	215-255
8	3 Segment Macro	No Function	0-1
		Macro 1 (slow to fast)	2-25
		Macro 2 (slow to fast)	26-50
		Macro 3 (slow to fast)	51-75
		Macro 4 (slow to fast)	76-100
		Macro 5 (slow to fast)	101-125
		Macro 6 (slow to fast)	126-150
		Macro 7 (slow to fast)	151-175
		Macro 8 (slow to fast)	176-200
		Macro 9 (slow to fast)	201-225
		Macro 10 (slow to fast)	226-255

XS LED RGB 9 Ch D Mode

DMX Channel	Function	Discription	Value
1	Dimmer	Red Dimmer Segment 1	0-255
2	Dimmer	Green Dimmer Segment 1	0-255
3	Dimmer	Blue Dimmer Segment 1	0-255
4	Dimmer	Red Dimmer Segment 2	0-255
5	Dimmer	Green Dimmer Segment 2	0-255
6	Dimmer	Blue Dimmer Segment 2	0-255
7	Dimmer	Red Dimmer Segment 3	0-255
8	Dimmer	Green Dimmer Segment 3	0-255
9	Dimmer	Blue Dimmer Segment 3	0-255