

## DMX Profile

---

### N-E Color FX18 Mode A

DMX Chanel	Function	Description	Value
1	LED Color	Red LED intensity	0-255
2	LED Color	Green LED Intensity	0-255
3	LED Color	Blue LED Intensity	0-255

### N-E Color FX18 Mode P

DMX Chanel	Function	Description	Value
1	Dimmer	Dimmer Off to Full	0-255
2	LED Color	Red LED intensity	0-255
3	LED Color	Green LED Intensity	0-255
4	LED Color	Blue LED Intensity	0-255
5	Strobe	Strobe (slow to fast)	0-196
		Random Strobe (slow to fast)	197-255
6	Macro	No Function	0-1
		Color Fade Full Bar(slow to fast)	2-19
		Color Snap Full Bar (slow to fast)	20-39
		Random Full Bar (slow to fast)	40-59
		Red Chase Each (slow to fast)	60-79
		Green Chase Each (slow to fast)	80-99
		Blue Chase Each (slow to fast)	100-119
		White Chase Each (slow to fast)	120-139
		Macro Effect 1	140-159
		Macro Effect 2	160-179
		Macro Effect 3	180-199
		Macro Effect 4	200-219
		Macro Effect 5	220-229
		Macro Effect 6	230-249
Macro Effect 7	250-255		

### N-E Color FX18 Mode F

DMX Chanel	Function	Description	Value
1	LED Color	Red LED intensity	0-255
2	LED Color	Green LED Intensity	0-255
3	LED Color	Blue LED Intensity	0-255
" "	" "	" "	" "
52	LED Color	Red LED intensity	0-255
53	LED Color	Green LED Intensity	0-255
54	LED Color	Blue LED Intensity	0-255